

SECTION 13850 (28 31 00)

FIRE DETECTION AND ALARM SYSTEM

ENGINEERING SPECIFICATION INTELLIGENT REPORTING FIRE DETECTION SYSTEM

PART 1 GENERAL

1.1 RELATED SECTIONS

- A. Section 13800 - Building Automation and Control.
- B. Section 13900 (21 00 00) - Fire Suppression.
- C. Section (27 15 00) - (Fire Alarm Communications Horizontal Cabling).

1.2 DESCRIPTION:

- A. This section of the specification includes the furnishing, installation, connection and testing of the microprocessor controlled, intelligent reporting fire alarm equipment required to form a complete, operative, coordinated system. It shall include, but not be limited to, alarm initiating devices, alarm notification appliances, Fire Alarm Control Panel (FACP), auxiliary control devices, annunciators, and wiring as shown on the drawings and specified herein.
- B. The fire alarm system shall comply with requirements of NFPA Standard 72 for Protected Premises Signaling Systems except as modified and supplemented by this specification. The system shall be electrically supervised and monitor the integrity of all conductors.
- C. The fire alarm system shall be manufactured by an ISO 9001 certified company and meet the requirements of BS EN9001: ANSI/ASQC Q9001-1994.
- D. The FACP and peripheral devices shall be manufactured 100% by a single U.S. manufacturer (or division thereof).
- E. The system and its components shall be Underwriters Laboratories, Inc. listed under the appropriate UL testing standard as listed herein for fire alarm applications and the installation shall be in compliance with the UL listing.
- F. The installing company shall employ NICET (minimum Level II Fire Alarm Technology) technicians on site to guide the final checkout and to ensure the systems integrity.

1.3 SCOPE:

- A. A new intelligent reporting, microprocessor controlled fire detection system shall be installed in accordance to the project specifications and drawings.

B. Basic Performance:

1. Alarm, trouble and supervisory signals from all intelligent reporting devices shall be encoded on NFPA Style 4 (Class B) Signaling Line Circuits (SLC).
2. Initiation Device Circuits (IDC) shall be wired Class A (NFPA Style D) as part of an addressable device connected by the SLC Circuit.
3. Notification Appliance Circuits (NAC) shall be wired Class A (NFPA Style Z) as part of an addressable device connected by the SLC Circuit.
4. On Style 6 or 7 (Class A) configurations a single ground fault or open circuit on the system Signaling Line Circuit shall not cause system malfunction, loss of operating power or the ability to report an alarm.
5. Alarm signals arriving at the FACP shall not be lost following a primary power failure (or outage) until the alarm signal is processed and recorded.
6. NAC speaker circuits shall be arranged such that there is a minimum of one speaker circuit per floor of the building or smoke zone which ever is greater.
7. Audio amplifiers and tone generating equipment shall be electrically supervised for normal and abnormal conditions.
8. NAC speaker circuits and control equipment shall be arranged such that loss of any one (1) speaker circuit will not cause the loss of any other speaker circuit in the system.
9. Two-way telephone communication circuits shall be supervised for open and short circuit conditions.

C. BASIC SYSTEM FUNCTIONAL OPERATION

When a fire alarm condition is detected and reported by one of the system initiating devices, the following functions shall immediately occur:

1. The system alarm LED on the system display shall flash.
2. A local piezo electric signal in the control panel shall sound.
3. A backlit LCD display shall indicate all information associated with the fire alarm condition, including the type of alarm point and its location within the protected premises.
4. Printing and history storage equipment shall log the information associated each new fire alarm control panel condition, along with time and date of occurrence.
5. All system output programs assigned via control-by-event interlock programming to be activated by the particular point in alarm shall be executed, and the associated system outputs (notification appliances and/or relays) shall be activated.

1.4 SUBMITTALS

A. General:

1. Two copies of all submittals shall be submitted to the Architect/Engineer for review.
2. All references to manufacturer's model numbers and other pertinent information herein is intended to establish minimum standards of performance, function and quality. Equivalent compatible UL-listed

equipment from other manufacturers may be substituted for the specified equipment as long as the minimum standards are met.

3. For equipment other than that specified, the contractor shall supply proof that such substitute equipment equals or exceeds the features, functions, performance, and quality of the specified equipment.

B. Shop Drawings:

1. Sufficient information, clearly presented, shall be included to determine compliance with drawings and specifications.
2. Include manufacturer's name(s), model numbers, ratings, power requirements, equipment layout, device arrangement, complete wiring point-to-point diagrams, and conduit layouts.
3. Show annunciator layout, configurations, and terminations.

C. Manuals:

1. Submit simultaneously with the shop drawings, complete operating and maintenance manuals listing the manufacturer's name(s), including technical data sheets.
2. Wiring diagrams shall indicate internal wiring for each device and the interconnections between the items of equipment.
3. Provide a clear and concise description of operation that gives, in detail, the information required to properly operate the equipment and system.

D. Software Modifications

1. Provide the services of a factory trained and authorized technician to perform all system software modifications, upgrades or changes. Response time of the technician to the site shall not exceed 4 hours.
2. Provide all hardware, software, programming tools and documentation necessary to modify the fire alarm system on site. Modification includes addition and deletion of devices, circuits, zones and changes to system operation and custom label changes for devices or zones. The system structure and software shall place no limit on the type or extent of software modifications on-site.

E. Certifications:

Together with the shop drawing submittal, submit a certification from the major equipment manufacturer indicating that the proposed supervisor of the installation and the proposed performer of contract maintenance is an authorized representative of the major equipment manufacturer. Include names and addresses in the certification.

1.5 GUARANTY:

All work performed and all material and equipment furnished under this contract shall be free from defects and shall remain so for a period of at least one (1) year from the date of acceptance. The full cost of maintenance, labor and materials

required to correct any defect during this one year period shall be included in the submittal bid.

1.6 POST CONTRACT MAINTENANCE:

- A. Complete maintenance and repair service for the fire alarm system shall be available from a factory trained authorized representative of the manufacturer of the major equipment for a period of five (5) years after expiration of the guaranty.
- B. As part of the bid/proposal, include a quote for a maintenance contract to provide all maintenance, tests, and repairs described below. Include also a quote for unscheduled maintenance/repairs, including hourly rates for technicians trained on this equipment, and response travel costs for each year of the maintenance period. Submittals that do not identify all post contract maintenance costs will not be accepted. Rates and costs shall be valid for the period of five (5) years after expiration of the guaranty.
- C. Maintenance and testing shall be on a semiannual basis or as required by the AHJ. A preventive maintenance schedule shall be provided by the contractor describing the protocol for preventive maintenance. The schedule shall include:
 - 1. Systematic examination, adjustment and cleaning of all detectors, manual fire alarm stations, control panels, power supplies, relays, waterflow switches and all accessories of the fire alarm system.
 - 2. Each circuit in the fire alarm system shall be tested semiannually.
 - 3. Each smoke detector shall be tested in accordance with the requirements of NFPA 72 Chapter 7.

1.7 POST CONTRACT EXPANSIONS:

- A. The contractor shall have the ability to provide parts and labor to expand the system specified, if so requested, for a period of five (5) years from the date of acceptance.
- B. As part of the submittal, include a quotation for all parts and material, and all installation and test labor as needed to increase the number of intelligent or addressable devices by ten percent (10%). This quotation shall include intelligent smoke detectors, intelligent heat detectors, addressable manual stations, addressable monitor modules and addressable modules equal in number to one tenth of the number required to meet this specification (list actual quantity of each type).
- C. The quotation shall include installation, test labor, and labor to reprogram the system for this 10% expansion. If additional FACP hardware is required, include the material and labor necessary to install this hardware.
- D. Do not include cost of conduit or wire or the cost to install conduit or wire except for labor to make final connections at the FACP and at each intelligent addressable device. Do not include the cost of conventional peripherals or the cost of initiating devices or notification appliances connected to the addressable monitor/control modules.

- E. Submittals that do not include this estimate of post contract expansion cost will not be accepted.

1.8 APPLICABLE STANDARDS AND SPECIFICATIONS:

The specifications and standards listed below form a part of this specification. The system shall fully comply with the latest issue of these standards, if applicable.

A. National Fire Protection Association (NFPA) - USA:

- No. 12 CO2 Extinguishing Systems (low and high)
- No. 12B Halon 1211 Extinguishing Systems
- No. 13 Sprinkler Systems
- No. 13A Halon 1301 Extinguishing Systems
- No. 15 Water Spray Systems
- No. 16 Foam/Water Deluge and Spray Systems
- No. 17 Dry Chemical Extinguishing Systems
- No. 17A Wet Chemical Extinguishing Systems
- ~~No. 2001 Clean Agent Extinguishing Systems~~
- No. 72 National Fire Alarm Code
- No. 101 Life Safety Code

Deleted: .

B. Underwriters Laboratories Inc. (UL) - USA:

- No. 268 Smoke Detectors for Fire Protective Signaling Systems
- No. 864 Control Units for Fire Protective Signaling Systems
- No. 268A Smoke Detectors for Duct Applications
- No. 521 Heat Detectors for Fire Protective Signaling Systems
- No. 464 Audible Signaling Appliances
- No. 38 Manually Actuated Signaling Boxes
- No. 346 Waterflow Indicators for Fire Protective Signaling Systems
- No. 1076 Control Units for Burglar Alarm Proprietary Protective Signaling Systems
- No. 1971 Visual Notification Appliances
- ~~No. 217 217 Smoke Detectors, Single and Multiple Station~~
- ~~No. 228 Door Closers - Holders for Fire Protective Signaling Systems~~
- ~~No. 1481 Power Supplies for Fire Protective Signaling Systems~~
- ~~No. 60951 Safety of Information Technology Equipment~~

C. Local and State Building Codes.

D. All requirements of the Authority Having Jurisdiction (AHJ).

1.9 APPROVALS:

Deleted: E. The Video Display Terminal (VDT) shall comply with Swedish magnetic emission and X-radiation guidelines MPR 1990:10.¶

- A. The system shall have proper listing and/or approval from the following nationally recognized agencies:

- UL Underwriters Laboratories Inc
- ULC Underwriters Laboratories Canada
- FM Factory Mutual

- B. The fire alarm control panel shall meet UL Standard 864 (Control Units) and UL Standard 1076 (Proprietary Burglar Alarm Systems).
- C. The system shall be listed by the national agencies as suitable for extinguishing release applications. The system shall support release of high and low pressure CO2.

- D. The system shall be certified for seismic applications in accordance with the International Building Code (IBC). For OSHPD applications in California the system shall be Pre-Approved for seismic applications. The basis for qualification of seismic approval shall be via shake table testing.

← Formatted: Normal

PART 2.0 PRODUCTS

2.1 EQUIPMENT AND MATERIAL, GENERAL:

- A. All equipment and components shall be new, and the manufacturer's current model. The materials, appliances, equipment and devices shall be tested and listed by a nationally recognized approvals agency for use as part of a protective signaling system, meeting the National Fire Alarm Code.
- B. All equipment and components shall be installed in strict compliance with manufacturers' recommendations. Consult the manufacturer's installation manuals for all wiring diagrams, schematics, physical equipment sizes, etc., before beginning system installation.
- C. All equipment shall be attached to walls and ceiling/floor assemblies and shall be held firmly in place (e.g., detectors shall not be supported solely by suspended ceilings). Fasteners and supports shall be adequate to support the required load.

2.2 CONDUIT AND WIRE:

- A. Conduit:
 - 1. Conduit shall be in accordance with The National Electrical Code (NEC), local and state requirements.
 - 2. Where required, all wiring shall be installed in conduit or raceway. Conduit fill shall not exceed 40 percent of interior cross sectional area where three or more cables are contained within a single conduit.
 - 3. Cable must be separated from any open conductors of power, or Class 1 circuits, and shall not be placed in any conduit, junction box or raceway containing these conductors, per NEC Article 760.
 - 4. Wiring for 24 volt DC control, alarm notification, emergency communication and similar power-limited auxiliary functions may be run in the same

Deleted: -55

conduit as initiating and signaling line circuits. All circuits shall be provided with transient suppression devices and the system shall be designed to permit simultaneous operation of all circuits without interference or loss of signals.

5. Conduit shall not enter the fire alarm control panel, or any other remotely mounted control panel equipment or backboxes, except where conduit entry is specified by the FACP manufacturer.
6. Conduit shall be 3/4-inch (19.1 mm) minimum.

B. Wire:

1. All fire alarm system wiring shall be new.
2. Wiring shall be in accordance with local, state and national codes (e.g., NEC Article 760) and as recommended by the manufacturer of the fire alarm system. Number and size of conductors shall be as recommended by the fire alarm system manufacturer, but not less than 18 AWG (1.02 mm) for Initiating Device Circuits, Signaling Line Circuits, and Notification Appliance Circuits.
3. All wire and cable shall be listed and/or approved by a recognized testing agency for use with a protective signaling system.
4. Wire and cable not installed in conduit shall have a fire resistance rating suitable for the installation as indicated in NFPA 70 (e.g., FPLR).
5. Wiring used for the multiplex communication circuit (SLC) shall be twisted and unshielded and support a minimum wiring distance of 12,500 feet. The design of the system shall permit use of IDC and NAC wiring in the same conduit with the SLC communication circuit.
6. All field wiring shall be electrically supervised for open circuit and ground fault.
7. The fire alarm control panel shall be capable of t-tapping Class B (NFPA Style 4) Signaling Line Circuits (SLCs). Systems that do not allow or have restrictions in, for example, the amount of t-taps, length of t-taps etc., are not acceptable.

Deleted: and

Deleted: ,

Deleted: 14 AWG (1.63 mm) for

C. Terminal Boxes, Junction Boxes and Cabinets:

All boxes and cabinets shall be UL listed for their use and purpose.

- D. Initiating circuits shall be arranged to serve like categories (manual, smoke, waterflow). Mixed category circuitry shall not be permitted except on signaling line circuits connected to intelligent reporting devices.
- E. The fire alarm control panel shall be connected to a separate dedicated branch circuit, maximum 20 amperes. This circuit shall be labeled at the main power distribution panel as FIRE ALARM. Fire alarm control panel primary power wiring shall be 12 AWG. The control panel cabinet shall be grounded securely to either a cold water pipe or grounding rod.

2.3 MAIN FIRE ALARM CONTROL PANEL OR NETWORK NODE:

- A. Main FACP or network node shall be a NOTIFIER Model NFS2-640 and shall contain a microprocessor based Central Processing Unit (CPU) and power

supply in an economical space saving single board design. The CPU shall communicate with and control the following types of equipment used to make up the system: intelligent addressable smoke and thermal (heat) detectors, addressable modules, printer, annunciators, and other system controlled devices.

B. Operator Control

1. Acknowledge Switch:
 - a. Activation of the control panel acknowledge switch in response to new alarms and/or troubles shall silence the local panel piezo electric signal and change the alarm and trouble LEDs from flashing mode to steady-ON mode. If multiple alarm or trouble conditions exist, depression of this switch shall advance the LCD display to the next alarm or trouble condition.
 - b. Depression of the Acknowledge switch shall also silence all remote annunciator piezo sounders.
2. Alarm Silence Switch:

Activation of the alarm silence switch shall cause all programmed alarm notification appliances and relays to return to the normal condition after an alarm condition. The selection of notification circuits and relays that are silenceable by this switch shall be fully field programmable within the confines of all applicable standards. The FACP software shall include silence inhibit and auto-silence timers.
3. Alarm Activate (Drill) Switch:

The Alarm Activate switch shall activate all notification appliance circuits. The drill function shall latch until the panel is silenced or reset.
4. System Reset Switch:

Activation of the System Reset switch shall cause all electronically-latched initiating devices, appliances or software zones, as well as all associated output devices and circuits, to return to their normal condition.
5. Lamp Test:

The Lamp Test switch shall activate all local system LEDs, light each segment of the liquid crystal display and display the panel software revision for service personal

C. System Capacity and General Operation

1. The control panel or each network node shall provide, or be capable of expansion to 636 intelligent/addressable devices.
2. The control panel or each network node shall include Form-C alarm, trouble, supervisory, and security relays rated at a minimum of 2.0 amps @ 30 VDC.
3. It shall also include four Class B (NFPA Style Y) or Class A (NFPA Style Z) programmable Notification Appliance Circuits
4. The Notification Appliance Circuits shall be programmable to Synchron~~ize~~ with System Sensor, Gentex and Wheelock Notification Appliances.
5. The system shall include a full featured operator interface control and annunciation panel that shall include a backlit Liquid Crystal Display (LCD),

individual color coded system status LEDs, and an alphanumeric keypad with easy touch rubber keys for the field programming and control of the fire alarm system.

6. The system shall be programmable, configurable, and expandable in the field without the need for special tools, PROM programmers or PC based programmers. It shall not require replacement of memory ICs to facilitate programming changes.
7. The system shall allow the programming of any input to activate any output or group of outputs. Systems that have limited programming (such as general alarm), have complicated programming (such as a diode matrix), or require a laptop personal computer are not considered suitable substitutes. The FACP shall support up to 20 logic equations, including "and," "or," and "not," or time delay equations to be used for advanced programming. Logic equations shall require the use of a PC with a software utility designed for programming.
8. The FACP or each network node shall provide the following features:
 - a. Drift compensation to extend detector accuracy over life. Drift compensation shall also include a smoothing feature, allowing transient noise signals to be filtered out.
 - b. Detector sensitivity test, meeting requirements of NFPA 72.
 - c. Maintenance alert, with two levels (maintenance alert/maintenance urgent), to warn of excessive smoke detector dirt or dust accumulation.
 - d. Nine sensitivity levels for alarm, selected by detector. The alarm level range shall be .5 to 2.35 percent per foot for photoelectric detectors and 0.5 to 2.5 percent per foot for ionization detectors. The system shall also support sensitive advanced detection laser detectors with an alarm level range of .02 percent per foot to 2.0 percent per foot. The system shall also include up to nine levels of Prealarm, selected by detector, to indicate impending alarms to maintenance personnel.
 - e. The ability to display or print system reports.
 - f. Alarm verification, with counters and a trouble indication to alert maintenance personnel when a detector enters verification 20 times.
 - g. PAS presignal, meeting NFPA 72 requirements.
 - h. Rapid manual station reporting (under 3 seconds) and shall meet NFPA 72 requirements for activation of notification circuits within 10 seconds of initiating device activation.
 - i. Periodic detector test, conducted automatically by the software.
 - j. Self optimizing pre-alarm for advanced fire warning, which allows each detector to learn its particular environment and set its prealarm level to just above normal peaks.
 - k. Cross zoning with the capability of counting: two detectors in alarm, two software zones in alarm, or one smoke detector and one thermal detector.
 - l. Walk test, with a check for two detectors set to same address.
 - m. Control-by-time for non-fire operations, with holiday schedules.
 - n. Day/night automatic adjustment of detector sensitivity.
 - o. Device blink control for sleeping areas.

Deleted: Chapter 7.

Deleted: 3

Deleted: 1

Deleted: 3-8.3

Deleted: Chapter 1

8. The FACP shall be capable of coding main panel node notification circuits in March Time (120 PPM), Temporal (NFPA 72), and California Code. Panel notification circuits (NAC 1,2,3 and 4) shall also support Two-Stage operation, Canadian Dual Stage (3 minutes) and Canadian Dual Stage (5 minutes). Two stage operation shall allow 20 Pulses Per Minute (PPM) on alarm and 120 PPM after 5 minutes or when a second device activates. Canadian Dual stage is the same as Two-Stage except will only switch to second stage by activation of Drill Switch 3 or 5 minute timer. The panel shall also provide a coding option that will synchronize specific strobe lights designed to accept a specific "sync pulse."
9. Network Communication
 - a. The FACP shall be capable of communicating on a Local Area Network (LAN), a firmware package that utilizes a peer-to-peer, inherently regenerative communication format and protocol.

Deleted: A-2-2.2.2

D. Central Microprocessor

1. The microprocessor shall be a state-of-the-art, high speed, 16-bit RISC device and it shall communicate with, monitor and control all external interfaces. It shall include an EPROM for system program storage, Flash memory for building-specific program storage, and a "watch dog" timer circuit to detect and report microprocessor failure.
2. The microprocessor shall contain and execute all control-by-event programs for specific action to be taken if an alarm condition is detected by the system. Control-by-event equations shall be held in non-volatile programmable memory, and shall not be lost even if system primary and secondary power failure occurs.
3. The microprocessor shall also provide a real-time clock for time annotation of system displays, printer, and history file. The time-of-day and date shall not be lost if system primary and secondary power supplies fail. The real time clock may also be used to control non-fire functions at programmed time-of-day, day-of-week, and day-of-year.
4. A special program check function shall be provided to detect common operator errors.
5. An auto-program (self-learn) function shall be provided to quickly install initial functions and make the system operational.
6. For flexibility and to ensure program validity, an optional Windows(TM) based program utility shall be available. This program shall be used to off-line program the system with batch upload/download, and have the ability to upgrade the manufacturers (FLASH) system code changes. This program shall also have a verification utility, which scans the program files, identifying possible errors. It shall also have the ability to compare old program files to new ones, identifying differences in the two files to allow complete testing of any system operating changes. This shall be in compliance with the NFPA 72 requirements for testing after system modification.

E. System Display

1. The system shall support the following display mode options:

- a. The CPU with no display option shall allow the fire alarm control panel to function as a data-gathering panel when the panel is connected to a network with a Network Control Station (NCS), ONYXWorks workstation or Network Control Annunciator (NCA). In this application, the NCS, OW or NCA shall provide all of the necessary controls and indicators to be used by the system operator. Programming of the CPU may be accomplished from the NCS or by use of a laptop PC with the software programming utility connected directly to the CPU.
- b. 80 character display option. The display shall include an 80-character backlit alphanumeric Liquid Crystal Display (LCD) and a full PC style QWERTY keypad.
- c. 640-character display option. The design of the CPU shall provide for a configuration with the 640 Character display mounted on the front of the CPU in place of the standard 80-character display.

1. When configured with a 640-character display option the system shall support distributed digital audio amplifiers on the digital audio loop

Formatted: Normal, Numbered + Level: 1 + Numbering Style: 1, 2, 3, ... + Start at: 1 + Alignment: Left + Aligned at: 90 pt + Tab after: 108 pt + Indent at: 108 pt

- 2. The display shall provide all the controls and indicators used by the system operator:
 - a. The 80-character display shall include the following operator control switches: ACKNOWLEDGE, ALARM SILENCE, ALARM ACTIVATE (drill), SYSTEM RESET, and LAMP TEST.
 - b. The 640-character display shall include the following operator control switches: ACKNOWLEDGE, ALARM SILENCE, ALARM ACTIVATE (drill), SYSTEM RESET, and LAMP TEST.
- 3. The display shall annunciate status information and custom alphanumeric labels for all intelligent detectors, addressable modules, internal panel circuits, and software zones.
- 4. The display shall also provide Light-Emitting Diodes.
 - a. The 80-character display shall provide 12 Light-Emitting-Diodes (LEDs), that indicate the status of the following system parameters: AC POWER, FIRE ALARM, PREALARM WARNING, SECURITY ALARM, SUPERVISORY SIGNAL, SYSTEM TROUBLE, DISABLED POINTS, ALARM SILENCED, Controls Active, Pre-Discharge, Discharge and Abort.
- 5. The 640-character display shall provide 11 Light-Emitting-Diodes (LEDs), that indicate the status of the following system parameters: AC POWER, FIRE ALARM, PREALARM WARNING, SECURITY ALARM, SUPERVISORY EVENT, SYSTEM TROUBLE, ALARM SILENCED, DISABLED POINTS, OTHER EVENTS, CPU FAILURE and Controls Active.
- 6. The display shall have QWERTY type keypad.

- a. The 80-character display keypad shall be an easy to use QWERTY type keypad, similar to a PC keyboard. This shall be part of the standard system and have the capability to command all system functions, entry of any alphabetic or numeric information, and field programming. Two different password levels shall be provided to prevent unauthorized system control or programming.
 - b. The 640-character display shall use 10 "soft" keys for screen navigation or to accomplish dedicated programming functions. Full programming access shall require use of a laptop and the proper programming utility.
7. The system shall support the display of battery charging current and voltage on the 80-character LCD display.

F. Signaling Line Circuits (SLC)

1. Each FACP or FACP network node shall support up to two SLCs. Each SLC interface shall provide power to and communicate with up to 159 intelligent detectors (ionization, photoelectric or thermal) and 159 intelligent modules (monitor or control) for a loop capacity of 318 devices. The addition of the optional second loop shall double the device capacity, supporting a total of 636 devices. Each SLC shall be capable of NFPA 72 Style 4, Style 6, or Style 7 (Class A or B) wiring.
2. CPU shall receive analog information from all intelligent detectors to be processed to determine whether normal, alarm, prealarm, or trouble conditions exist for each detector. The software shall automatically maintain the detector's desired sensitivity level by adjusting for the effects of environmental factors, including the accumulation of dust in each detector. The analog information shall also be used for automatic detector testing and for the automatic determination of detector maintenance requirements.

G. Serial Interfaces

1. The system shall include two serial EIA-232 interfaces. Each interface shall be a means of connecting UL Listed Information Technology Equipment (ITE) peripherals.
 - a. One EIA-232 interface shall be used to connect an UL-Listed 40 or 80 column printer. Printers that are not UL-Listed are not considered acceptable substitutes.
 - b. One EIA-232 interface shall be used to connect an UL-Listed 40 or 80 column printer. Printers that are not UL-Listed are not considered acceptable substitutes.
 - c. One EIA-232 interface shall be used to connect a UL-listed CRT terminal. This interface shall include special protocol methods that allow off-site monitoring of the FACP over standard dial-up phone lines. This ancillary capability shall allow remote readout of all status information, including analog values, and shall not interfere with or degrade FACP operations when used. It shall allow remote FACP

Acknowledge, Reset, or Signal Silence in this mode. It shall also allow adjustment of detector sensitivity and readout of the history file.

- d. The system shall include an EIA-485 port for the serial connection of optional annunciators and remote LCD displays.
- e. The EIA-485 interface may be used for network connection to a proprietary-receiving unit.

H. Digital Voice Command Center

1. The Digital Voice Command Center located with the FACP, shall contain all equipment required for all audio control, emergency telephone system control, signaling and supervisory functions. This shall include speaker zone indication and control, telephone circuit indication and control, digital voice units, microphone and main telephone handset. The DVC shall support up to 8 channels of voice when configured with Digital Audio Amplifiers and 4 channels of voice when employing the optional analog output card. Each DVC shall support up to 32 digital audio amplifiers.
2. Function: The Voice Command Center equipment shall perform the following functions:
 - a. Operate as a supervised multi-channel emergency voice communication system.
 - b. Operate as a two-way emergency telephone system control center.
 - c. Audibly and visually annunciate the active or trouble condition of every speaker circuit and emergency telephone circuit.
 - d. Audibly and visually annunciate any trouble condition for digital tone and voice units required for normal operation of the system.
 - e. Provide all-call Emergency Paging activities through activation of a single control switch.
 - f. As required, provide vectored paging control to specific audio zones via dedicated control switches.
 - g. Provide a factory recorded "library" of voice messages and tones in standard WAV. File format, which may be edited and saved on a PC running a current Windows® operating system.
 - h. Provide a software utility capable of off-line programming for the VCC operation and the audio message files. This utility shall support the creation of new programs as well as editing and saving existing program files. Uploading or downloading the VCC shall not inhibit the emergency operation of other nodes on the fire alarm network.
 - i. Support an optional mode of operation with four analog audio outputs capable of being used with UL 864 fire-listed analog audio amplifiers and SCL controlled switching.
 - j. The Digital Voice Command shall be modular in construction, and shall be capable of being field programmable without requiring the return of any components to the manufacturer and without requiring use of any external computers or other programming equipment.
 - k. The Digital Voice Command and associated equipment shall be protected against unusually high voltage surges or line transients.

S.

Formatted: French (France)

Deleted: Voice Command Center (VCC)¶

- ¶
1. The facility shall have an emergency voice alarm communication system. Digitally stored message sequences shall notify the building occupants that a fire or life safety condition has been reported. A Message generator shall be capable of automatically distributing up to four (4) simultaneous, unique messages to appropriate audio zones within the facility based on the type and location of the initiating event. The Fire Command Center (FCC) shall also support Emergency manual voice announcement capability for both system wide or selected audio zones, and shall include provisions for the system operator to override automatic messages system wide or in selected zones.¶
 - a. The digital audio message generator shall be of reliable, non-moving parts, and support the digital storage of at least 16 or 32 minutes of tones and emergency messages, shall support programming options to string audio segments together to create up to 1000 messages, or to loop messages and parts of messages to repeat for pre-determined cycles or indefinitely.¶
 - b. The audio portion of the system shall sound the proper audio signal (consisting of tone, voice, or tone and voice) to the appropriate zones. ¶
 - c. Notification Appliance Circuits (NAC) speaker circuits shall be arranged such that there is a minimum of one speaker circuit per floor of the building or smoke zone which ever is greater.¶
 - d. Audio amplifiers and tone generating equipment shall be electrically supervised for normal and abnormal conditions.¶
 - e. Speaker circuits shall be electrically supervised for open and short circuit conditions. If a short circuit exists on a speaker circuit, it shall not be possible to activate that circuit.¶
 - f. Speaker circuits shall be either 25 VRMS or 70VRMS. Speaker circuits shall have 20% spare capacity for future expansion or increased power output requirement

2. The emergency voice alarm communication system shall incorporate a Two-way emergency telephone communication system.
 - a. Two-way emergency telephone communication circuits shall be supervised for open and short circuit conditions.
 - b. Two-way emergency telephone (Fire Fighter Telephone) communication shall be supported between the Digital Voice Command Center and up to seven (7) remote Fire Fighter's Telephone locations simultaneously on a telephone riser.
 - c. Means shall be provided to connect FFT voice communications to the speaker circuits in order to allow voice paging over the speaker circuit from a telephone handset.

Deleted: Audio

I. Audio Amplifiers

1. The Audio Amplifiers will provide Audio Power (@25 Volt RMS or 70 RMS) for distribution to speaker circuits.
2. Multiple audio amplifiers may be mounted in a single enclosure, either to supply incremental audio power, or to function as an automatically switched backup amplifier(s).
3. The audio amplifier shall include an integral power supply, and shall provide built-in LED indicators for the following conditions:
 - Earth Fault on DAP A (Digital Audio Port A)
 - Earth Fault on DAP B (Digital Audio Port B)
 - Audio Amplifier Failure Detected Trouble
 - Active Alarm Bus input
 - Audio Detected on Aux Input A
 - Audio Detected on Aux Input B
 - Audio Detected on Firefighter's Telephone Riser
 - Receiving Audio from digital audio riser
 - Short circuit on speaker circuit 1
 - Short circuit on speaker circuit 2
 - Short circuit on speaker circuit 3
 - Short circuit on speaker circuit 4
 - Data Transmitted on DAP A
 - Data Received on DAP A
 - Data Transmitted on DAP B
 - Data Received on DAP B
 - Board failure
 - Active fiber optic media connection on port A (fiber optic media applications)
 - Active fiber optic media connection on port B (fiber optic media applications)
 - Power supply Earth Fault
 - Power supply 5V present
 - Power supply conditions – Brownout, High Battery, Low Battery, Charger Trouble
4. The audio amplifier shall provide the following built-in controls:
 - Amplifier Address Selection Switches

- Signal Silence of communication loss annunciation Reset
- Level adjustment for background music
- Enable/Disable for Earth Fault detection on DAP A
- Enable/Disable for Earth Fault detection on DAP A
- Switch for 2-wire/4-wire FFT riser

5. Adjustment of the correct audio level for the amplifier shall not require any special tools or test equipment.

6. Includes audio input and amplified output supervision, back up input, and automatic switch over function, (if primary amplifier should fail).

7. System shall be capable of backing up digital amplifiers.

8. One-to-one backup shall be provided by either a plug-in amplifier card or a designated backup amplifier of identical model as the primary amplifier.

9. One designated backup amplifier shall be capable of backing up multiple primary amplifiers mounted in the same or adjacent cabinets.

10. Multi-channel operation from a single amplifier shall be supported by the addition of an optional plug-in amplifier card.

← --- **Formatted:** Indent: First line: 36 pt

← --- **Formatted:** Normal

J. Audio Message Generator (Prerecorded Voice)/Speaker Control:

1. Each initiating zone or intelligent device shall interface with an emergency voice communication system capable of transmitting a prerecorded voice message to all speakers in the building.

2. Actuation of any alarm initiating device shall cause a prerecorded message to sound over the speakers. The message shall be repeated four (4) times. Pre- and post-message tones shall be supported.

3. A built-in microphone shall be provided to allow paging through speaker circuits.

4. System paging from emergency telephone circuits shall be supported.

5. The audio message generator shall have the following indicators and controls to allow for proper operator understanding and control:

← --- **Formatted:** Spec: Heading 4 [A.], Numbered + Level: 1 + Numbering Style: A, B, C, ... + Start at: 10 + Alignment: Left + Aligned at: 9.35 pt + Tab after: 36.35 pt + Indent at: 36.35 pt

LED Indicators:

- Lamp Test
- Trouble
- Off-Line Trouble
- Microphone Trouble
- Phone Trouble
- Busy/Wait
- Page Inhibited
- Pre/Post Announcement Tone

← --- **Formatted:** French (France)

K. Controls with associated LED Indicators:

1. Speaker Switches/Indicators

a. The speaker circuit control switches/indicators shall include visual indication of active and trouble status for each speaker circuit in the system.

b. The speaker circuit control panel shall include switches to manually activate or deactivate each speaker circuit in the system.

← --- **Formatted:** Bullets and Numbering

2. Emergency Two-Way Telephone Control Switches/Indicators

- a. The emergency telephone circuit control panel shall include visual indication of active and trouble status for each telephone circuit in the system.
- b. The telephone circuit control panel shall include switches to manually activate or deactivate each telephone circuit in the system.

← - - - Formatted: Normal

← - - - Formatted: Normal

← - - - Formatted: Normal

I. Enclosures:

1. The control panel shall be housed in a UL-listed cabinet suitable for surface or semi-flush mounting. The cabinet and front shall be corrosion protected, given a rust-resistant prime coat, and manufacturer's standard finish.
2. The back box and door shall be constructed of 0.060 steel with provisions for electrical conduit connections into the sides and top.
3. The door shall provide a key lock and shall include a glass or other transparent opening for viewing of all indicators. For convenience, the door may be site configured for either right or left hand hinging.

J. Power Supply:

1. A high tech off-line switching power supply shall be available for the fire alarm control panel or network node and provide 6.0 amps of available power for the control panel and peripheral devices.
2. Provisions will be made to allow the audio-visual power to be increased as required by adding modular expansion audio-visual power supplies.
3. Positive-Temperature-Coefficient (PTC) thermistors, circuit breakers, or other over-current protection shall be provided on all power outputs. The power supply shall provide an integral battery charger for use with batteries up to 55 AH or may be used with an external battery and charger system. Battery arrangement may be configured in the field.
4. The power supply shall continuously monitor all field wires for earth ground conditions, and shall have the following LED indicators:

Ground Fault LED
AC Power Fail LED
NAC on LED (4)

5. The main power supply shall operate on 120 VAC, 60 Hz, and shall provide all necessary power for the FACP.
6. The main power supply shall provide a battery charger using dual-rate charging techniques for fast battery recharge and be capable of charging batteries up to 200 AH.

7. All circuits shall be power-limited, per UL864 requirements.

K. Auxiliary Field Power Supply - Addressable

1. The auxiliary addressable power supply is a remote 24 VDC power supply used to power Notification Devices and field devices that require regulated 24VDC power. The power supply shall also include and charge backup batteries.
2. The addressable power supply for the fire alarm system shall provide up a minimum of 6.0 amps of 24 volt DC regulated power for Notification Appliance Circuit (NAC) power or 5 amps of 24 volt DC general power. The power supply shall have an additional .5 amp of 24 VDC auxiliary power for use within the same cabinet as the power supply. It shall include an integral charger designed to charge 7.0 - 25.0 amp hour batteries.
3. The addressable power supply shall provide four individually addressable Notification Appliance Circuits that may be configured as two Class "A" and two Class "B" or four Class "B" only circuits. All circuits shall be power-limited per UL 864 requirements.
4. The addressable power supply shall provide built-in synchronization for certain Notification Appliances on each circuit without the need for additional synchronization modules. The power supply's output circuits shall be individually selected for synchronization. A single addressable power supply shall be capable of supporting both synchronized and non-synchronized Notification Devices at the same time.
5. The addressable power supply shall operate on 120 or 240 VAC, 50/60 Hz.
6. The interface to the power supply from the Fire Alarm Control Panel (FACP) shall be via the Signaling Line Circuit (SLC) or other multiplexed means. Power supplies that do not use an intelligent interface are not suitable substitutes. The required wiring from the FACP to the addressable power supply shall be a single unshielded twisted pair wire. Data on the SLC shall be transmitted between 24 VDC, 5 VDC and 0 VDC at approximately 3.33k baud.
7. The addressable power supply shall supervise for battery charging failure, AC power loss, power brownout, battery failure, NAC loss, and optional ground fault detection. In the event of a trouble condition, the addressable power supply shall report the incident and the applicable address to the FACP via the SLC.
8. The addressable power supply shall have an AC Power Loss Delay option. If this option is utilized and the addressable power supply experiences an AC power loss, reporting of the incident to the FACP will be delayed. A delay time of eight or sixteen hours shall be Dip-switch selected.
9. The addressable power supply shall have an option for Canadian Trouble Reporting and this option shall be Dip-switch selectable.
10. The addressable power supply mounts in either the FACP backbox or it's own dedicated surface mounted backbox with cover.
11. Each of the power supply's four output circuits shall be DIP-switch selected for Notification Appliance Circuit or General Purpose 24 VDC power. Any output circuit shall be able to provide up to 2.5 amps of 24 VDC power.
12. The addressable power supply's output circuits shall be individually supervised when they are selected to be either a Notification Appliance Circuit when wired Class "A" or by the use of an end-of-line resistor. When

- the power supply's output circuit is selected as General 24VDC power, the circuit shall be individually supervised when an end-of-line relay is used.
13. When selected for Notification Appliance Circuits, the output circuits shall be individually DIP-switch selectable for Steady, March Time, Dual Stage or Temporal.
 14. When selected as a Notification Appliance Circuit, the output circuits of the addressable power supply shall have the option to be coded by the use of a universal zone coder.
 15. The addressable power supply shall interface and synchronize with other power supplies of the same type. The required wiring to interface multiple addressable power supplies shall be a single unshielded, twisted pair wire.
 16. An individual or multiple interfaced addressable power supplies shall have the option to use an external charger for battery charging. Interfaced power supplies shall have the option to share backup battery power.

L. Field Charging Power Supply (FCPS)

The FCPS-~~24S6/8~~ is a device designed for use as either a remote 24 volt power supply or used to power Notification Appliances.

1. The FCPS-~~246~~ shall offer up to 6.0 amps (4.0 amps continuous) of regulated 24 volt power. It shall include an integral charger designed to charge ~~up to 18.0 amp hour batteries and to support up to 60 hour standby.~~ The FCPS-24S8 shall offer up to 8.0 amps (6.0 amps continuous) of regulated 24 volt power. It shall include an integral charger designed to charge up to 18.0 amp hour batteries and to support up to 60 hour standby.
2. The Field Charging Power Supply shall have two input triggers. The input trigger shall be a Notification Appliance Circuit (from the fire alarm control panel) or a relay. Four outputs (two Style Y or Z and two style Y) shall be available for connection to the Notification devices.
3. The FCPS shall include an attractive surface mount backbox.
4. The Field Charging Power Supply shall include the ability to delay the AC fail delay per NFPA requirements.
5. The FCPS include power limited circuitry, per ~~UL~~ standards.

Deleted: 7

Deleted: 1995

M. Specific System Operations

1. Smoke Detector Sensitivity Adjust: A means shall be provided for adjusting the sensitivity of any or all addressable intelligent detectors in the system from the system keypad. Sensitivity range shall be within the allowed UL window and have a minimum of 9 levels.
2. Alarm Verification: Each of the intelligent addressable smoke detectors in the system may be independently selected and enabled to be an alarm verified detector. The alarm verification delay shall be programmable from 5 to 30 seconds and each detector shall be able to be selected for verification. The FACP shall keep a count of the number of times that each detector has entered the verification cycle. These counters may be displayed and reset by the proper operator commands.
3. Point Disable: Any addressable device or conventional circuit in the system may be enabled or disabled through the system keypad.

4. Point Read: The system shall be able to display or print the following point status diagnostic functions:
 - a. Device status
 - b. Device type
 - c. Custom device label
 - d. View analog detector values
 - e. Device zone assignments
 - f. All program parameters
5. System Status Reports: Upon command from an operator of the system, a status report will be generated and printed, listing all system status.
6. System History Recording and Reporting: The fire alarm control panel shall contain a history buffer that will be capable of storing up to 800 events. Up to 200 events shall be dedicated to alarm and the remaining events are general purpose. Systems that do not have dedicated alarm storage, where events are overridden by non-alarm type events, are not suitable substitutes. Each of these activations will be stored and time and date stamped with the actual time of the activation. The contents of the history buffer may be manually reviewed, one event at a time, or printed in its entirety. The history buffer shall use non-volatile memory. Systems that use volatile memory for history storage are not acceptable substitutes.
7. Automatic Detector Maintenance Alert: The fire alarm control panel shall automatically interrogate each intelligent detector and shall analyze the detector responses over a period of time. If any intelligent detector in the system responds with a reading that is above or below normal limits, then the system will enter the trouble mode, and the particular detector will be annunciated on the system display, and printed on the optional printer. This feature shall in no way inhibit the receipt of alarm conditions in the system, nor shall it require any special hardware, special tools or computer expertise to perform.
8. Pre-Alarm Function: The system shall provide two levels of pre-alarm warning to give advance notice of a possible fire situation. Both pre-alarm levels shall be fully field adjustable. The first level shall give an audible indication at the panel. The second level shall give an audible indication and may also activate control relays. The system shall also have the ability to activate local detector sounder bases at the pre-alarm level, to assist in avoiding nuisance alarms.
9. Software Zones: The FACP shall provide 100 software zones, 10 additional special function zones, 10 releasing zones, and 20 logic zones.
10. The fire alarm control panel shall include a walk test feature. It shall include the ability to test initiating device circuits and notification appliance circuits from the field without returning to the panel to reset the system. Operation shall be as follows:
 - a. Alarming an initiating device shall activate programmed outputs, which are selected to participate in walk test, for 3 seconds.
 - b. Introducing a trouble into the initiating device shall activate the programmed outputs for 8 seconds.
 - c. All devices tested in walk test shall be recorded in the history buffer.

11. Waterflow Operation
An alarm from a waterflow detection device shall activate the appropriate alarm message on the main panel display, turn on all programmed notification appliance circuits and shall not be affected by the signal silence switch.
12. Supervisory Operation
An alarm from a supervisory device shall cause the appropriate indication on the system display, light a common supervisory LED, but will not cause the system to enter the trouble mode.
13. Signal Silence Operation
The FACP shall have the ability to program each output circuit (notification, relay, speaker etc) to deactivate upon depression of the signal silence switch.
14. Non-Alarm Input Operation
Any addressable initiating device in the system may be used as a non-alarm input to monitor normally open contact type devices. Non-alarm functions are a lower priority than fire alarm initiating devices.

2.4 SYSTEM COMPONENTS:

A. Programmable Electronic Sounders:

1. Electronic sounders shall operate on 24 VDC nominal.
2. Electronic sounders shall be field programmable without the use of special tools, at a sound level of at least 90 dBA measured at 10 feet from the device.
3. Shall be flush or surface mounted as shown on plans.

B. Speakers:

1. All speakers shall operate on 25 VRMS or 70 VRMS with field selectable output taps from 0.5 to 2.0 Watts.
2. Speakers in corridors and public spaces shall produce a nominal sound output of 84 dBA at 10 feet (3m).
3. Frequency response shall be a minimum of 400 HZ to 4000 HZ.
4. The back of each speaker shall be sealed to protect the speaker cone from damage and dust.

C. Strobe lights shall meet the requirements of the ADA, UL Standard 1971, be fully synchronized, and shall meet the following criteria:

1. The maximum pulse duration shall be 2/10 of one second.
2. Strobe intensity shall meet the requirements of UL 1971.
3. The flash rate shall meet the requirements of UL 1971.

D. Manual Fire Alarm Stations

1. Manual fire alarm stations shall be non-code, non-breakglass type, equipped with key lock so that they may be tested without operating the handle.

Deleted: 15. Combo Zone¶
A special type code shall be available to allow waterflow and supervisory devices to share a common addressable module. Waterflow devices shall be wired in parallel, supervisory devices in series.¶

2. Stations must be designed such that after an actual activation, they cannot be restored to normal except by key reset.
3. An operated station shall automatically condition itself so as to be visually detected, as operated, at a minimum distance of 100 feet (30.5 m) front or side.
4. Manual stations shall be constructed of high impact Lexan, with operating instructions provided on the cover. The word FIRE shall appear on the manual station in letters one half inch (12.7 mm) in size or larger.

E. Conventional Photoelectric Area Smoke Detectors

1. Photoelectric smoke detectors shall be a 24 VDC, two wire, ceiling-mounted, light scattering type using an LED light source.
2. Each detector shall contain a remote LED output and a built-in test switch.
3. Detector shall be provided on a twist-lock base.
4. It shall be possible to perform a calibrated sensitivity and performance test on the detector without the need for the generation of smoke. The test method shall test all detector circuits.
5. A visual indication of an alarm shall be provided by dual latching Light Emitting Diodes (LEDs), on the detector, which may be seen from ground level over 360 degrees. These LEDs shall flash at least every 10 seconds, indicating that power is applied to the detector.
6. The detector shall not go into alarm when exposed to air velocities of up to 3000 feet (914.4 m) per minute.
7. The detector screen and cover assembly shall be easily removable for field cleaning of the detector chamber.
8. All field wire connections shall be made to the base through the use of a clamping plate and screw.

F. Conventional Ionization Type Area Smoke Detectors

1. Ionization type smoke detectors shall be a two wire, 24 VDC type using a dual unipolar chamber.
2. Each detector shall contain a remote LED output and a built-in test switch.
3. Detector shall be provided on a twist-lock base.
4. It shall be possible to perform a calibration sensitivity and performance test on the detector without the need for the generation of smoke.
5. A visual indication of an alarm shall be provided by dual latching Light Emitting Diodes (LEDs) over 360 degrees, on the detector, which may be seen from ground level. This LED shall flash every 10 seconds, indicating that power is applied to the detector.
6. The detector shall not alarm when exposed to air velocities of up to 1,200 feet (365.76 m) per minute. The detector screen and cover assembly shall be easily removable for field cleaning of the detector chamber.
7. All field wire connections shall be made to the base through the use of a clamping plate and screw.

G. Duct Smoke Detectors

Duct smoke detectors shall be a 24 VDC type with visual alarm and power indicators, and a reset switch. Each detector shall be installed upon the composite supply/return air ducts(s), with properly sized air sampling tubes.

H. Projected Beam Detectors

1. The projected beam type shall be a 4-wire 24 VDC device.
2. The detector shall be listed to UL 268 and shall consist of a separate transmitter and receiver capable of being powered separately or together.
3. The detector shall operate in either a short range (30' - 100') or long range (100' - 330') mode.
4. The temperature range of the device shall be -22 degrees F to 131 degrees F.
5. The detector shall feature a bank of four alignment LEDs on both the receiver and the transmitter that are used to ensure proper alignment of unit without special tools.
6. Beam detectors shall feature automatic gain control which will compensate for gradual signal deterioration from dirt accumulation on lenses.
7. The unit shall be both ceiling and wall mountable.
8. The detector shall have the ability to be tested using calibrated test filters or magnet activated remote test station.

I. Automatic Conventional Heat Detectors

1. Automatic heat detectors shall have a combination rate of rise and fixed temperature rated at 135 degrees Fahrenheit (57.2 Celsius) for areas where ambient temperatures do not exceed 100 degrees (37.7 Celsius), and 200 degrees (93.33 Celsius) for areas where the temperature does not exceed 150 degrees (65.5 Celsius).
2. Automatic heat detectors shall be a low profile, ceiling mount type with positive indication of activation.
3. The rate of rise element shall consist of an air chamber, a flexible metal diaphragm, and a factory calibrated, moisture-proof, trouble free vent, and shall operate when the rate of temperature rise exceeds 15 degrees F (9.4 degrees C) per minute.
4. The fixed temperature element shall consist of a fusible alloy retainer and actuator shaft.
5. Automatic heat detectors shall have a smooth ceiling rating of 2500 square feet (762 square meters).

J. Waterflow Indicator:

1. Waterflow Switches shall be an integral, mechanical, non-coded, non-accumulative retard type.
2. Waterflow Switches shall have an alarm transmission delay time which is conveniently adjustable from 0 to 60 seconds. Initial settings shall be 30-45 seconds.
3. All waterflow switches shall come from a single manufacturer and series.
4. Waterflow switches shall be provided and connected under this section but installed by the mechanical contractor.

5. Where possible, locate waterflow switches a minimum of one (1) foot from a fitting which changes the direction of the flow and a minimum of three (3) feet from a valve.

K. Sprinkler and Standpipe Valve Supervisory Switches:

1. Each sprinkler system water supply control valve riser, zone control valve, and standpipe system riser control valve shall be equipped with a supervisory switch. Standpipe hose valves, and test and drain valves shall not be equipped with supervisory switches.
2. PIV (post indicator valve) or main gate valves shall be equipped with a supervisory switch.
3. The switch shall be mounted so as not to interfere with the normal operation of the valve and adjusted to operate within two revolutions toward the closed position of the valve control, or when the stem has moved no more than one-fifth of the distance from its normal position.
4. The supervisory switch shall be contained in a weatherproof aluminum housing, which shall provide a 3/4 inch (19 mm) conduit entrance and incorporate the necessary facilities for attachment to the valves.
5. The switch housing shall be finished in red baked enamel.
6. The entire installed assembly shall be tamper proof and arranged to cause a switch operation if the housing cover is removed, or if the unit is removed from its mounting.
7. Valve supervisory switches shall be provided and connected under this section and installed by mechanical contractor.
 - a. This unit shall provide for each zone: alarm indications, using a red alarm a yellow trouble long-life LEDs and control switches for the control of fire alarm control panel functions. The annunciator will also have an ON-LINE LED, local piezo electric signal, local acknowledge/lamp test switch, and custom slide-in zone/function identification labels.
 - b. Switches shall be available for remote annunciation and control of output points in the system, system acknowledge, telephone zone select, speaker select, global signal silence, and global system reset within the confines of all applicable standards.

L. Alphanumeric LCD Type Annunciator:

1. The alphanumeric display annunciator shall be a supervised, remotely located back-lit LCD display containing a minimum of eighty (80) characters for alarm annunciation in clear English text.
2. The LCD annunciator shall display all alarm and trouble conditions in the system.
3. An audible indication of alarm shall be integral to the alphanumeric display.
4. The display shall be UL listed for fire alarm application.
5. It shall be possible to connect up to 32 LCD displays and be capable of wiring distances up to 6,000 feet from the control panel.
6. The annunciator shall connect to a separate, dedicated "terminal mode" EIA-485 interface. This is a two-wire loop connection and shall be capable

of distances to 6,000 feet. Each terminal mode LCD display shall mimic the main control panel.

7. The system shall allow a minimum of 32 terminal mode LCD annunciators ~~and, shall be capable of the following system functions: Acknowledge, Signal Silence and Reset, which shall be protected from unauthorized use by a keyswitch or password.~~
8. The LED annunciator shall offer an interface to a graphic style annunciator and provide each of the features listed above.

Deleted: . Up to 10 LCD annunciators

M. Portable Emergency Telephone Handset Jack

1. Portable emergency telephone handset jacks shall be flush mounted on stainless steel plates as indicated on the plans. Jacks shall be approved for emergency telephone system application.
2. Insertion of a portable handset plug into a jack shall send a signal to the fire command center, which shall audibly and visually indicate the on-line condition, and shall sound a "ring" indication in the handset.
3. The two-way emergency telephone system shall support a minimum of seven (7) handsets on line without degradation of the signal.

N. Fixed Emergency Telephone Handset

1. The telephone cabinet shall be painted red and clearly labeled as "Emergency Telephone." The cabinets shall be located where shown on drawings.
2. The handset cradle shall have a switch connection so that lifting the handset off of the cradle shall send a signal to the fire command center, which shall audibly and visually indicate its on-line (off-hook) condition.
3. On activating the remote phone, the phone earpiece shall sound a telephone ring signal until the master handset is lifted.
4. The two-way emergency telephone system shall support a minimum of seven (7) handsets on line without degradation of the signal.

- O. All interfaces and associated equipment are to be protected so that they will not be affected by voltage surges or line transients consistent with UL standard 864.

P. Universal Digital Alarm Communicator Transmitter (UDACT). The UDACT is an interface for communicating digital information between a fire alarm control panel and an UL-Listed central station.

1. The UDACT shall be compact in size, mounting in a standard module position of the fire alarm control cabinet. Optionally, the UDACT shall have the ability for remote mounting, up to 6,000 feet from the fire alarm control panel. The wire connections between the UDACT and the control panel shall be supervised with one pair for power and one pair for multiplexed communication of overall system status. Systems that utilize relay contact closures are not acceptable.
2. The UDACT shall include connections for dual telephone lines (with voltage detect), per UL/NFPA/FCC requirements. It shall include the ability for split reporting of panel events up to three different telephone numbers.

3. The UDACT shall be completely field programmable from a built-in keypad and 4 character red, seven segment display.
4. The UDACT shall be capable of transmitting events in at least 15 different formats. This ensures compatibility with existing and future transmission formats.
5. Communication shall include vital system status such as:
 - Independent Zone (Alarm, trouble, non-alarm, supervisory)
 - Independent Addressable Device Status
 - AC (Mains) Power Loss
 - Low Battery and Earth Fault
 - System Off Normal
 - 12 and 24 Hour Test Signal
 - Abnormal Test Signal (per UL requirements)
 - EIA-485 Communications Failure
 - Phone Line Failure

6. The UDACT shall support independent zone/point reporting when used in the Contact ID format. In this format the UDACT shall support transmission of up to 2,040 points. This enables the central station to have exact details concerning the origin of the fire or response emergency.

Deleted: 6.

Formatted: Bullets and Numbering

7. AN IP Communicator option shall be available to interface to the UDACT and be capable of transmitting signals over the internet/intranet to a compatible receiver.

Formatted: Normal, Indent: Left: 36 pt, Hanging: 27.35 pt

Q. Field Wiring Terminal Blocks

For ease of service all panel I/O wiring terminal blocks shall be removable, plug-in types and have sufficient capacity for #18 to #12 AWG wire. Terminal blocks that are permanently fixed are not acceptable.

R. Printer

1. The printer shall provide hard-copy printout of all changes in status of the system and shall time-stamp such printouts with the current time-of-day and date. The printer shall be standard carriage with 80-characters per line and shall use standard pin-feed paper. The printer shall be enclosed in a separate cabinet suitable for placement on a desktop or table. The printer shall communicate with the control panel using an interface complying with Electrical Industries Association standard EIA-232D. Power to the printer shall be 120 VAC @ 60 Hz.
2. The system shall have a strip printer capable of being mounted directly in the main FACP enclosure. Alarms shall be printed in easy-to-read RED, other messages, such as a trouble, shall be printed in BLACK. This printer shall receive power from the system power supply and shall operate via battery back-up if AC mains are lost. The strip printer shall be UL 864 listed.

3. The system shall have a strip printer capable of being mounted directly in the main FACP enclosure. Alarms shall be printed in easy-to-read RED, other messages, such as a trouble, shall be printed in BLACK. This printer shall receive power from the system power supply and shall operate via battery back-up if AC mains are lost. The strip printer shall be UL 864 listed.

2.5 SYSTEM COMPONENTS - ADDRESSABLE DEVICES

A. Addressable Devices - General

1. Addressable devices shall use simple to install and maintain decade, decimal address switches. Devices shall be capable of being set to an address in a range of 001 to 159.
2. Addressable devices, which use a binary-coded address setting method, such as a DIP-switch, are not an allowable substitute. Addressable devices that require the address be programmed using a special tool or programming utility are not an allowable substitute.
3. Detectors shall be intelligent (analog) and addressable, and shall connect with two wires to the fire alarm control panel Signaling Line Circuits.
4. Addressable smoke and thermal detectors shall provide dual alarm and power/polling LEDs. Both LEDs shall flash green under normal conditions, indicating that the detector is operational and in regular communication with the control panel, and both LEDs shall be placed into steady red illumination by the control panel, indicating that an alarm condition has been detected. If required, the LED flash shall have the ability to be removed from the system program. An output connection shall also be provided in the base to connect an external remote alarm LED.
5. The fire alarm control panel shall permit detector sensitivity adjustment through field programming of the system. The panel on a time-of-day basis shall automatically adjust sensitivity.
6. Using software in the FACP, detectors shall automatically compensate for dust accumulation and other slow environmental changes that may affect their performance. The detectors shall be listed by UL as meeting the calibrated sensitivity test requirements of NFPA Standard 72.
7. The detectors shall be ceiling-mount and shall include a separate twist-lock base with tamper proof feature. Base options shall include a sounder base with a built-in (local) sounder rated at 85 DBA minimum, a relay base and an isolator base designed for Style 7 applications.
8. The detectors shall provide a test means whereby they will simulate an alarm condition and report that condition to the control panel. Such a test may be initiated at the detector itself (by activating a magnetic switch) or initiated remotely on command from the control panel.
9. Detectors shall also store an internal identifying type code that the control panel shall use to identify the type of device (ION, PHOTO, THERMAL).
10. Detectors will operate in an analog fashion, where the detector simply measures its designed environment variable and transmits an analog value to the FACP based on real-time measured values. The FACP software, not the detector, shall make the alarm/normal decision, thereby allowing the

Deleted: S. . Video Display Terminal¶

- ¶ 1. The Video Display Terminal shall provide a visual display and an audible alert of all changes in status of the system and shall annotate such displays with the current time-of-day and date.¶
2. The Video Display Terminal shall be enclosed in a cabinet suitable for placement on a desktop or table.¶
3. A detachable keyboard shall be provided that may be used for programming, testing, and control of the system. Individual keys shall be provided on the keyboard for the ACKNOWLEDGE, RESET, LAMP TEST, SYSTEM TEST, and SIGNAL SILENCE functions of the control panel.¶
4. The video display terminal shall include a count of all alarms and troubles in the system, as well as a count of all alarms and trouble requiring acknowledgment. These counts shall be continuously displayed during all FACP operations.¶

Deleted: , Chapter 7

Deleted: s

sensitivity of each detector to be set in the FACP program and allowing the system operator to view the current analog value of each detector.

11. Addressable devices shall store an internal identifying code that the control panel shall use to identify the type of device.
12. A magnetic test switch shall be provided to test detectors and modules. Detectors shall report an indication of an analog value reaching 100% of the alarm threshold.
13. Addressable modules shall mount in a 4-inch square (101.6 mm square), 2-1/8 inch (54 mm) deep electrical box. An optional surface mount Lexan enclosure shall be available.

B. Addressable Manual Fire Alarm Box (manual station)

1. Addressable manual fire alarm boxes shall, on command from the control panel, send data to the panel representing the state of the manual switch and the addressable communication module status. They shall use a key operated test-reset lock, and shall be designed so that after actual emergency operation, they cannot be restored to normal use except by the use of a key.
2. All operated stations shall have a positive, visual indication of operation and utilize a key type reset.
3. Manual fire alarm boxes shall be constructed of Lexan with clearly visible operating instructions provided on the cover. The word FIRE shall appear on the front of the stations in raised letters, 1.75 inches (44 mm) or larger.

C. Intelligent Photoelectric Smoke Detector

1. The detectors shall use the photoelectric (light-scattering) principal to measure smoke density and shall, on command from the control panel, send data to the panel representing the analog level of smoke density.

D. Intelligent Laser Photo Smoke Detector

1. The intelligent laser photo smoke detector shall be a spot type detector that incorporates an extremely bright laser diode and an integral lens that focuses the light beam to a very small volume near a receiving photo sensor. The scattering of smoke particles shall activate the photo sensor.
2. The laser detector shall have conductive plastic so that dust accumulation is reduced significantly.
3. The intelligent laser photo detector shall have nine sensitivity levels and be sensitive to a minimum obscuration of 0.02 percent per foot.
4. The laser detector shall not require expensive conduit, special fittings or PVC pipe.
5. The intelligent laser photo detector shall support standard, relay, isolator and sounder detector bases.
6. The laser photo detector shall not require other cleaning requirements than those listed in NFPA 72. Replacement, refurbishment or specialized cleaning of the detector head shall not be required.
7. The laser photo detector shall include two bicolor LEDs that flash green in normal operation and turn on steady red in alarm.

Deleted: 3

E. Intelligent Ionization Smoke Detector

1. The detectors shall use the dual-chamber ionization principal to measure products of combustion and shall, on command from the control panel, send data to the panel representing the analog level of products of combustion.

F. Intelligent Multi Criteria Acclimating Detector

1. The intelligent multi criteria Acclimate detector shall be an addressable device that is designed to monitor a minimum of photoelectric and thermal technologies in a single sensing device. The design shall include the ability to adapt to its environment by utilizing a built-in microprocessor to determine it's environment and choose the appropriate sensing settings. The detector design shall allow a wide sensitivity window, no less than 1 to 4% per foot obscuration. This detector shall utilize advanced electronics that react to slow smoldering fires and thermal properties all within a single sensing device.
2. The microprocessor design shall be capable of selecting the appropriate sensitivity levels based on the environment type it is in (office, manufacturing, kitchen etc.) and then have the ability to automatically change the setting as the environment changes (as walls are moved or as the occupancy changes).
3. The intelligent multi criteria detection device shall include the ability to combine the signal of the thermal sensor with the signal of the photoelectric signal in an effort to react hastily in the event of a fire situation. It shall also include the inherent ability to distinguish between a fire condition and a false alarm condition by examining the characteristics of the thermal and smoke sensing chambers and comparing them to a database of actual fire and deceptive phenomena.

G. Intelligent Thermal Detectors

1. Thermal detectors shall be intelligent addressable devices rated at 135 degrees Fahrenheit (58 degrees Celsius) and have a rate-of-rise element rated at 15 degrees F (9.4 degrees C) per minute. It shall connect via two wires to the fire alarm control panel signaling line circuit.

H. Intelligent Duct Smoke Detector

1. The smoke detector housing shall accommodate either an intelligent ionization detector or an intelligent photoelectric detector, of that provides continuous analog monitoring and alarm verification from the panel.
2. When sufficient smoke is sensed, an alarm signal is initiated at the FACP, and appropriate action taken to change over air handling systems to help prevent the rapid distribution of toxic smoke and fire gases throughout the areas served by the duct system.

H. Advanced Multi-Criteria Intelligent Detector

1. The intelligent multi criteria IntelliQuad detector shall be an addressable device combining four sensing elements in a single sensing device providing the ability to detect all four major elements of a fire. The

detector design shall allow sensitivity setting between 1% to 4% per foot obscuration.

- The detector shall include a photoelectric sensing element, thermal sensing element, IR (Infrared) sensing element and CO (carbon monoxide) sensor

Formatted: Normal

J. Addressable Dry Contact Monitor Module

- Addressable monitor modules shall be provided to connect one supervised IDC zone of conventional alarm initiating devices (any N.O. dry contact device) to one of the fire alarm control panel SLCs.
- The IDC zone shall be suitable for Style D or Style B operation. An LED shall be provided that shall flash under normal conditions, indicating that the monitor module is operational and in regular communication with the control panel.
- For difficult to reach areas, the monitor module shall be available in a miniature package and shall be no larger than 2-3/4 inch (70 mm) x 1-1/4 inch (31.7 mm) x 1/2 inch (12.7 mm). This version need not include Style D or an LED.
- For multiple dry contact monitoring a module shall be available that provides 10 Style B or 5 Style D input circuits.

Deleted: ¶

- Hostile-Area Smoke Detector¶
¶
 - The detector shall be designed to provide early warning smoke detection in environments where traditional smoke detectors are not practical.¶
 - The detector shall have a filter system to remove particles down to 25 microns.¶
 - This filter system shall remove unwanted airborne particles and water mist. This shall allow the detector to operate in environments where traditional smoke detectors would have nuisance alarms.¶
 - The filter system shall consist of 2 filters one of which is field replaceable.¶
 - The filter system shall have an intake fan to draw air and smoke through the filters into the sensing chamber.¶
 - The filter system shall be supervised so that if the filter is clogged or the fan fails the control panel reports trouble.¶
 - The filter system shall be powered from 24 VDC separate from the SLC communications.¶
 - The detector shall utilize a photoelectric sensing chamber.¶

Formatted: Normal

K. Two Wire Detector Monitor Module

- Addressable monitor modules shall be provided to connect one supervised IDC zone of conventional 2-wire smoke detectors or alarm initiating devices (any N.O. dry contact device).
- The IDC zone may be wired for Class A or B (Style D or Style B) operation. An LED shall be provided that shall flash under normal conditions, indicating that the monitor module is operational and in regular communication with the control panel.
- For multiple 2-wire smoke detector circuit monitoring a module shall be available that provides 6 Style B or 3 Style D input circuits.

Formatted: Normal

L. Addressable Control Module

- Addressable control modules shall be provided to supervise and control the operation of one conventional NACs of compatible, 24 VDC powered, polarized audio/visual notification appliances.
- The control module NAC may be wired for Style Z or Style Y (Class A/B) with a current rating of 2 Amps for Style Z and 3 Amps for Style Y. For speaker applications the module is rated for 50 watts at 25 or 70.7 Vrms.
- Audio/visual power shall be provided by a separate supervised power circuit from the main fire alarm control panel or from a supervised UL listed remote power supply.
- For multiple circuit control a module shall be available that provides 6 Style

B or 3 Style D control circuits.

Formatted: Normal

M. Addressable Relay Module

1. Addressable Relay Modules shall be available for HVAC control and other building functions. The module shall provide two form C relays rated at up to 3 Amps resistive and up to 2.0 Amps inductive. The relay coil shall be magnetically latched to reduce wiring connection requirements, and to insure that 100% of all auxiliary devices energize at the same time on the same pair of wires.
2. For multiple relay control a module shall be available that provides 6 programmable Form-C relays.

Deleted: Addressable control modules shall be provided to supervise and control the operation of one conventional NACs of compatible, 24 VDC powered, polarized audio/visual notification appliances. ¶
2. The control module NAC may be wired for Style Z or Style Y (Class A/B) with up to 1 amp of inductive A/V signal, or 2 amps of resistive A/V signal operation. ¶
3. Audio/visual power shall be provided by a separate supervised power circuit from the main fire alarm control panel or from a supervised UL listed remote power supply.¶
4. The control module shall be suitable for pilot duty applications and rated for a minimum of 0.6 amps at 30 VDC.

L. Addressable Releasing Control Module

1. An addressable FlashScan releasing module shall be available to supervise and control compatible releasing agent solenoids.
2. The module shall operate on a redundant protocol for added protection.
3. The module shall be configurable for Style Z or Style Y (Class A/B) and support one 24 volt or two 12 volt solenoids.

Deleted: 1.

Formatted: Bullets and Numbering

Formatted: Indent: Left: 36 pt

Deleted: <#>Addressable Relay Modules shall be available for HVAC control and other building functions. The relay shall be form C and rated for a minimum of 2.0 Amps resistive or 1.0 Amps inductive. The relay coil shall be magnetically latched to reduce wiring connection requirements, and to insure that 100% of all auxiliary relay or NACs may be energized at the same time on the same pair of wires.

Deleted: <#>¶

Formatted: Normal, Numbered + Level: 1 + Numbering Style: A, B, C, ... + Start at: 10 + Alignment: Left + Aligned at: 9.35 pt + Tab after: 36.35 pt + Indent at: 36.35 pt

Formatted: Bullets and Numbering

Formatted: Normal

N. Isolator Module

1. Isolator modules shall be provided to automatically isolate wire-to-wire short circuits on an SLC Class A or Class B branch. The isolator module shall limit the number of modules or detectors that may be rendered inoperative by a short circuit fault on the SLC loop segment or branch. At least one isolator module shall be provided for each floor or protected zone of the building.
2. If a wire-to-wire short occurs, the isolator module shall automatically open-circuit (disconnect) the SLC. When the short circuit condition is corrected, the isolator module shall automatically reconnect the isolated section.
3. The isolator module shall not require address-setting, and its operations shall be totally automatic. It shall not be necessary to replace or reset an isolator module after its normal operation.
4. The isolator module shall provide a single LED that shall flash to indicate that the isolator is operational and shall illuminate steadily to indicate that a short circuit condition has been detected and isolated.

O. Smoke Control Annunciator

1. On/Auto/Off switches and status indicators (LEDS) shall be provided for monitoring and manual control of each fan, damper, HVAC control unit,

stairwell pressurization fan, and smoke exhaust fan. To ensure compliance the units supplied shall meet the following UL categories : UUKL, PAZX, UDTZ, QVAX as well as the requirements of NFPA 90A, HVAC, and NFPA 92A & 92B, Smoke Control. The control System shall be field programmable for either 90A operation or 92A/B operation to allow for future use and system expansion.

2. The OFF LED shall be Yellow, the ON LED shall be green, the Trouble/Fault LED shall be Amber/Orange for each switch. The Trouble/Fault indicator shall indicate a trouble in the control and/or monitor points associated with that switch. In addition, each group of eight switches shall have two LEDs and one momentary switch which allow the following functions: An Amber LED to indicate an OFF-NORMAL switch position, in the ON or OFF position; A Green LED to indicate ALL AUTO switch position; A Local Acknowledge/Lamp Test momentary switch.
3. Each switch shall have the capability to monitor and control two addressable inputs and two addressable outputs. In all modes, the ON and OFF indicators shall continuously follow the device status not the switch position. Positive feedback shall be employed to verify correct operation of the device being controlled. Systems that indicate on/off/auto by physical switch position only are not acceptable.
4. All HVAC switches (i.e., limit switches, vane switches, etc.) shall be provided and installed by the HVAC contractor.
5. It shall be possible to meet the requirements mentioned above utilizing wall mounted custom graphic.

2.6 BATTERIES:

- A. The battery shall have sufficient capacity to power the fire alarm system for not less than twenty-four hours plus 5 minutes of alarm upon a normal AC power failure.
- B. The batteries are to be completely maintenance free. No liquids are required. Fluid level checks for refilling, spills, and leakage shall not be required.
- C. If necessary to meet standby requirements, external battery and charger systems may be used.

PART 3.0 - EXECUTION

3.1 INSTALLATION:

- A. Installation shall be in accordance with the NEC, NFPA 72, local and state codes, as shown on the drawings, and as recommended by the major equipment manufacturer.
- B. All conduit, junction boxes, conduit supports and hangers shall be concealed in finished areas and may be exposed in unfinished areas. Smoke detectors shall not be installed prior to the system programming and test period. If construction is ongoing during this period, measures shall be taken to protect smoke detectors from contamination and physical damage.

- C. All fire detection and alarm system devices, control panels and remote annunciators shall be flush mounted when located in finished areas and may be surface mounted when located in unfinished areas.
- D. Manual fire alarm boxes shall be suitable for surface mounting or semi-flush mounting as shown on the plans, and shall be installed not less than 42 inches (1067 mm), nor more than 48 inches (122 mm) above the finished floor.

3.2 TEST:

The service of a competent, factory-trained engineer or technician authorized by the manufacturer of the fire alarm equipment shall be provided to technically supervise and participate during all of the adjustments and tests for the system. All testing shall be in accordance with NFPA 72, Chapter 7.

- A. Before energizing the cables and wires, check for correct connections and test for short circuits, ground faults, continuity, and insulation.
- B. Close each sprinkler system flow valve and verify proper supervisory alarm at the FACP.
- C. Verify activation of all waterflow switches.
- D. Open initiating device circuits and verify that the trouble signal actuates.
- E. Open and short signaling line circuits and verify that the trouble signal actuates.
- F. Open and short notification appliance circuits and verify that trouble signal actuates.
- G. Ground all circuits and verify response of trouble signals.
- H. Check presence and audibility of tone at all alarm notification devices.
- I. Check installation, supervision, and operation of all intelligent smoke detectors using the walk test.
- J. Each of the alarm conditions that the system is required to detect should be introduced on the system. Verify the proper receipt and the proper processing of the signal at the FACP and the correct activation of the control points.
- K. When the system is equipped with optional features, the manufacturer's manual shall be consulted to determine the proper testing procedures. This is intended to address such items as verifying controls performed by individually addressed or grouped devices, sensitivity monitoring, verification functionality and similar.

3.3 FINAL INSPECTION:

- A. At the final inspection, a factory-trained representative of the manufacturer of the major equipment shall demonstrate that the system functions properly in every respect.

3.4 INSTRUCTION:

- A. Instruction shall be provided as required for operating the system. Hands-on demonstrations of the operation of all system components and the entire system including program changes and functions shall be provided.
- B. The contractor and/or the systems manufacturer's representatives shall provide a typewritten "Sequence of Operation."

END OF SECTION